

Time: 3 Hours

DECEMBER 2013

Max. Marks: 100

PLEASE WRITE YOUR ROLL NO. AT THE SPACE PROVIDED ON EACH PAGE IMMEDIATELY AFTER RECEIVING THE QUESTION PAPER.

NOTE: There are 9 Questions in all.

- Question 1 is compulsory and carries 20 marks. Answer to Q.1 must be written in the space provided for it in the answer book supplied and nowhere else.
- The answer sheet for the Q.1 will be collected by the invigilator after 45 minutes of the commencement of the examination.
- Out of the remaining EIGHT Questions answer any FIVE Questions. Each question carries 16 marks.
- Any required data not explicitly given, may be suitably assumed and stated.

Q.1 Choose the correct or the best alternative in the following: (2×10)

a. A light ray is incident from glass to air. If $n_1=1.5$ and $n_2=1$, the critical angle is

- (A) 41.81° (B) 81.41°
(C) 14.18° (D) 18.14°

b. For a fiber cable $n_{\text{core}} = 1.5$ and $n_{\text{cladding}} = 1.48$. The numerical aperture is

- (A) 0.442 (B) 0.244
(C) 0 (D) 1

c. An optical fiber has a diameter of $50\ \mu\text{m}$, $n_1=1.48$, $n_2=1.46$ and $\lambda=0.82\ \mu\text{m}$. The number of modes will be

- (A) 3801 (B) 1083
(C) 100 (D) 1000

d. A multimode step index optical fiber with relative refractive index difference of 1.5% and core refractive index 1.48 is to be used for single mode operation. If $\lambda=0.85\ \mu\text{m}$, the maximum core diameter will be

- (A) 1.3 m (B) 1.3 mm
(C) 1.3 μm (D) 2.6 μm

e. A fiber has an average loss of 3dB/km at 900 nm. The length over which the power decreases by 50% is

- (A) 1km (B) 2km
(C) 3km (D) 4km

Code: AE75 Subject: OPTOELECTRONICS AND COMMUNICATION

- f. The radiative and non radiative recombination life times of minority carriers in the active region of a heterjunction LED are 60 nsec and 90 nsec respectively. The total carrier recombination life time is
- (A) 63 nsec (B) 36 nsec
(C) 10 nsec (D) 100 nsec
- g. A PIN photodiode is fabricated by GaAs has bandgap energy of 1.43eV at 300°k. It's upper cut-off wavelength is
- (A) 867nm (B) 768nm
(C) 10nsec (D) None of these
- h. For a 2 × 2 fiber coupler, if the input power is 200 μW and throughput power is 90 μW, the insertion loss will be
- (A) 6.43 dB (B) 4.63 dB
(C) 3.4 dB (D) None of these
- i. Which of the following fibers are suitable for WDM of signals:
- (A) Dispersion optimized (B) Dispersion – shifted
(C) Dispersion flattened (D) Any fiber
- j. Photons having an energy of 1.53×10^{-19} joules are incident on a photodiode having responsivity of 0.65A/W. If the output power is 10 μW, the generated photocurrent is
- (A) 6nA (B) 6.5μA
(C) 6mA (D) None of these

**Answer any FIVE Questions out of EIGHT Questions.
Each question carries 16 marks.**

- Q.2** a. List out limitations of optical fiber communication systems. (6)
- b. A step index multimode fiber with a numerical aperture of a 0.20 supports approximately 1000 modes at an 850nm wavelength.
(i) What is the diameter of its core?
(ii) How many modes does the fiber support at 1320nm? (6)
- c. A fiber has normalized frequency $V = 26.6$ and the operating wavelength is 1300nm. If the radius of the fiber core is 25 μm, compute the numerical aperture. (4)
- Q.3** a. Explain the pulse dispersion in optical fibers with suitable diagram. (6)

Code: AE75 Subject: OPTOELECTRONICS AND COMMUNICATION

- b. A continuous 12 km long optical fiber link has a loss of 1.5 dB/km. (6)
 (i) What is the minimum optical power level that must be launched into the fiber to maintain an optical power level of 0.3 μ W at the receiving end?
 (ii) What is the required input power if the fiber has a loss of 2.5 dB/km?
- c. An LED operating at 850 nm has a spectral width of 45 nm. What is the pulse spreading in ns/km due to material dispersion? (4)
- Q.4** a. Show that the optical power emitted from an LED is $\frac{P_{int}}{n(n+1)^2}$ where P_{int} is the internally generated optical power, n is the refractive index of LED material. (8)
- b. Describe the emission patterns of different types of LED and LASER diodes. (8)
- Q.5** a. Briefly explain the source-to-fiber power launching. (8)
- b. A single mode fiber has a normalized frequency $V = 2.40$, a core refractive index $n_1 = 1.47$, a cladding refractive index $n_2 = 1.465$ and a core diameter $2a = 9 \mu\text{m}$. Let us find the insertion losses of a fiber joint having a lateral offset of 1 μm . (8)
- Q.6** a. Draw and explain the schematic diagram of a typical optical receiver. (8)
- b. Explain the circuit diagram of high impedance bipolar transistor amplifier. List the benefits of a transimpedance amplifier. (8)
- Q.7** a. Write short notes of any **TWO**. (16)
 (i) Carrier power
 (ii) Photodetector and pre-amplifier noises
 (iii) Relative intensity noise (RIN)
- Q.8** a. Write short notes on (8)
 (i) RZ codes
 (ii) Block codes
- b. With help of neat sketch. Explain the basic setup for an automatic-repeat-request (ARQ) error correction scheme. (8)
- Q.9** a. Describe (i) SONET/SDH Networks (ii) Frame format of SONET/SDH (10)
- b. A 2x2 biconical tapered fiber coupler has an input optical power level of $P_0 = 200 \mu\text{W}$. The output powers at the other three ports are $P_1 = 90 \mu\text{W}$, $P_2 = 85 \mu\text{W}$ and $P_3 = 6.3 \mu\text{W}$. Find:- (6)
 (i) Coupling ratio
 (ii) Excess loss