

- Q.2
- List out limitations of optical fiber communication systems.
 - A step index multimode fiber with a numerical aperture of a 0.20 supports approximately 1000 modes at an 850nm wavelength.
 - What is the diameter of its core?
 - How many modes does the fiber support at 1320nm?
 - A fiber has normalized frequency $V = 26.6$ and the operating wavelength is 1300nm. If the radius of the fiber core is 25 μm , compute the numerical aperture.

Answer:

Ⓐ Limitations of OFC:
 High initial cost, Maintenance & repair cost, jointing & testing proced-ures, Tensile stress, Short links, Short links, Fiber losses (03)

→ Brief explanation about each (04)

Ⓑ (i) NO of modes

$$M = \frac{1}{2} \left[\frac{\pi a}{\lambda} \cdot NA \right]^2$$

$$1000 = \frac{1}{2} \left[\frac{\pi a}{(850 \times 10^{-9})} \times 0.20 \right]^2 \quad (03)$$

$$a = 60.49 \mu\text{m}$$

$$(ii) M = \frac{1}{2} \left[\frac{\pi \times 60.49 \times 10^{-6}}{1550 \times 10^{-9}} \times 0.20 \right]^2 = 300.63 \quad (03)$$

Ⓒ $V = 26.6, \lambda = 1300 \times 10^{-9}$ (194/8) (27)

$$a = 25 \times 10^{-6} \text{ m}$$

$$V = \frac{2\pi a}{\lambda} \cdot NA \Rightarrow NA = V \cdot \frac{\lambda}{2\pi a}$$

$$NA = 26.6 \frac{1300 \times 10^{-9}}{2\pi \times 25 \times 10^{-6}} = 0.220 \quad (04)$$

- Q.3 b. A continuous 12 km long optical fiber link has a loss of 1.5 dB/km.
- What is the minimum optical power level that must be launched into the fiber to maintain an optical power level of $0.3 \mu\text{W}$ at the receiving end?
 - What is the required input power if the fiber has a loss of 2.5 dB/km?
- c. An LED operating at 850 nm has a spectral width of 45 nm. What is the pulse spreading in ns/km due to material dispersion?

Answer:

(b) $z = 12 \text{ km}, \alpha = 1.5 \text{ dB/km}, P(0) = 0.3 \mu\text{W}$
 (i) $\alpha = 10 \times \frac{1}{z} \log \left(\frac{P(0)}{P(z)} \right)$
 $1.5 = 10 \times \frac{1}{12} \log \left(\frac{0.3 \mu\text{W}}{P(z)} \right)$ (03)
 $P(z) = 4.76 \times 10^{-9} \text{ W}$
 (ii) $2.5 = 10 \times \frac{1}{12} \log \left(\frac{P(0)}{4.76 \times 10^{-9}} \right)$ (03)
 1/1 power, $P(0) = 4.76 \mu\text{W}$
 (c) $\lambda = 850 \text{ nm}, \sigma = 45 \text{ nm}$
 $\sigma_m = \sigma \cdot LM$, Let $L = 1 \text{ m}$
 mat. disp. const, $D_{\text{mat}} = -\frac{\lambda}{c} \cdot \frac{d^2 n}{d\lambda^2}$
 For LED source operating at 850 nm,
 $\left| \lambda^2 \frac{d^2 n}{d\lambda^2} \right| = 0.025$
 $M = \frac{1}{c\lambda} \left| \lambda^2 \frac{d^2 n}{d\lambda^2} \right| = \frac{1}{(3 \times 10^8) (850)} \times 0.025$ (3)
 $= 9.8 \text{ ps/nm/km}$
 $\sigma_m = 45 \times 1 \times 9.8 = 441 \text{ ps/km}$ (04)

- Q.4** a. Show that the optical power emitted from an LED is $\frac{P_{int}}{n(n+1)^2}$ where P_{int} is the internally generated optical power, n is the reference index of LED material.
- b. Describe the emission patterns of different types of LED and LASER diodes.

Answer:

Q.4 Main steps in the derivation

(a) $\eta_{int} = \frac{R_r}{R_r + R_{nr}}$, $\tau_{nr} = \frac{n}{R_{nr}}$

$$= \frac{1}{1 + \frac{R_{nr}}{R_r}}$$

$$\frac{1}{\tau} = \frac{1}{\tau_r} + \frac{1}{\tau_{nr}}, \eta_{int} = \frac{\tau}{\tau_r}$$

$$P_{int} = R_r \cdot h\nu$$

$$P = \frac{1}{n(n+1)^2} \cdot P_{int}$$

(b) Emission patterns of LED & LASER

LED v/s LASER Diode

Parameter	LED	LD
Principle of operation	Spontaneous emission	Stimulated emission
output beam	Non-coherent	coherent
Transmission distance	smaller	greater
Coupling efficiency	Very low	High
Cost	Low	High

Q.5 a. Briefly explain the source-to-fiber power launching.

Answer: 5.1 of Text Book

b. A single mode fiber has a normalized frequency $V = 2.40$, a core refractive index $n_1 = 1.47$, a cladding refractive index $n_2 = 1.465$ and a core diameter $2a = 9 \mu\text{m}$. Let us find the insertion losses of a fiber joint having a lateral offset of $1 \mu\text{m}$.

Answer: Page Number 230 of Text Book

Q.6 a. Draw and explain the schematic diagram of a typical optical receiver.

Answer: 7.1.3 of Text Book

b. Explain the circuit diagram of high impedance bipolar transistor amplifier. List the benefits of a transimpedance amplifier.

Answer: 7.4.2, 7.4.3 of Text Book

Q.7 a. Write short notes of any **TWO**.

(ii) Photodetector and pre-amplifier noises

(iii) Relative intensity noise (RIN)

Answer: Page Number 361-363 of Text Book

Q.8 a. Write short notes on

(i) RZ codes

(ii) Block codes

Answer: 8.2.2, 8.2.3 of Text Book

b. With help of neat sketch. Explain the basic setup for an automatic-repeat-request (ARQ) error correction scheme.

Answer: 8.3 of Text Book

Q.9 a. Describe (i) SONET/SDH Networks (ii) Frame format of SONET/SDH

Answer:

* Voice, video, data, internet & data from LANs, MANs & WANs will be transported over a SONET or a SDH network.

Adv. of SONET/SDH:

- Reduced cost
- Integrated N/W elements
- Offers network survivability feat - reses
- compatible with legacy & future networks.
- Remote operation capabilities'

- b. A 2×2 biconical tapered fiber coupler has an input optical power level of $P_0 = 200 \mu\text{W}$. The output powers at the other three ports are $P_1 = 90 \mu\text{W}$, $P_2 = 85 \mu\text{W}$ and $P_3 = 6.3 \mu\text{W}$. Find:-
- Coupling ratio
 - Excess loss

Answer: Page Number 387-388 of Text Book

Text Book

Optical Fiber Communications, Gerd Keiser, 3rd Edition, McGraw Hill Publications,
2000